



Westinghouse

INNOVATION YOU CAN BE SURE OF

Consumer Guide

Inverter Generator Comparison

	 Westinghouse 2400i	 Honda EU22i	 Yamaha EF2000iS
Engine Displacement	79 cc	121 cc	79 cc
Rated Electrical Output	2,100 Watts	1,800 Watts	1,600 Watts
Maximum Electrical Output	2,400 Watts	2,200 Watts	2,000 Watts
Rated AC Electrical Voltage	240 Volts	240 Volts	230 Volts
240 Volt AC Socket Outlets	2	2	1
240 Volt AC Overload Reset	Push Button	Engine Restart	Engine Restart
12 Volt DC Cig. Lighter Socket	Yes	No	No
Digital Multifunction Display	Yes	No	No
Single-Sided Control Access	Yes	No	Yes
Dimensions L x W x H	50 x 34 x 44 cm	51 x 29 x 43 cm	49 x 28 x 45 cm
Weight (Dry)	20 kg	21 kg	20 kg
Fuel Tank Capacity	5 Litres	3.6 Litres	4.4 Litres
Fuel Level Gauge	Yes	No	Yes
Fuel Shutoff Valve (Independent)	Yes	Yes	Yes
Run Time @ 400 Watts	16 Hours	8 Hours #	10.5 Hours
Run Time @ 1,600 Watts	5 Hours	4 Hours ^	4.2 Hours
Noise Level @ 400 Watts (7 m)	52 dB(A)	Not Stated	51.5 dB(A)
Noise Level @ 1,600 Watts (7 m)	61 dB(A)	Not Stated	61 dB(A)
Protective Dust Cover Included	Yes	No	No
Warranty (Personal Use) *	2 Years	4 Years Δ	4 Years
Warranty (Commercial Use) *	1 Year	1 Year	1 Year
Recommended Retail Price	\$1,399	\$2,099	\$2,249

* Conditions apply. # @ 450 Watts. ^ @ 1,800 Watts.

Δ To qualify, the generator must be serviced for the entire warranty period by an authorised Honda dealer.

Source: Manufacturers' websites as at 18 June 2020.

Power - when you need it - where you need it

westinghouseoutdoorpower.com.au