



Westinghouse

INNOVATION YOU CAN BE SURE OF

Consumer Guide

Inverter Generator Comparison

	 Westinghouse iGen2500	 Honda EU22i	 Yamaha EF2200iS
Engine Displacement	98 cc	121 cc	79 cc
Rated Electrical Output	2,200 Watts	1,800 Watts	1,800 Watts
Maximum Electrical Output	2,500 Watts	2,200 Watts	2,200 Watts
Rated AC Electrical Voltage	240 Volts	240 Volts	230 Volts
240 Volt AC Socket Outlets	1	2	2
240 Volt AC Overload Reset	Engine Restart	Engine Restart	Push Button
12 Volt DC Cig. Lighter Socket	No	No	Yes
USB Fast Charger Socket	Yes	No	No
Digital Hour Meter	Yes	No	No
Single-Sided Control Access	No	No	No
Dimensions L x W x H	50 x 29 x 45 cm	51 x 29 x 43 cm	56 x 30 x 47 cm
Weight (Dry)	21.5 kg	21 kg	25 kg
Fuel Tank Capacity	4.3 Litres	3.6 Litres	4.7 Litres
Fuel Level Gauge	No	No	Yes
Fuel Shutoff Valve	Yes	Yes	Yes
Run Time @ 400 Watts	9 Hours #	8 Hours #	10.5 Hours #
Run Time @ 1,600 Watts	4.5 Hours ^	4 Hours ^	Not Stated
Noise Level @ 400 Watts (7 m)	52 dB(A)	Not Stated	57 dB(A) #
Noise Level @ 1,600 Watts (7 m)	61 dB(A)	Not Stated	65 dB(A) ^
Warranty (Personal Use) *	2 Years	4 Years Δ	4 Years
Warranty (Commercial Use) *	1 Year	1 Year	1 Year
Recommended Retail Price	\$1,499	\$2,099	\$2,399

* Conditions apply. # @ 450 Watts. ^ @ 1,800 Watts.

Δ To qualify, the generator must be serviced for the entire warranty period by an authorised Honda dealer.

Source: Manufacturers' websites as at 18 June 2020.

2020-06-18

Power - when you need it - where you need it

westinghouseoutdoorpower.com.au